


# RS 4.4T-2 Actuator and Sensor Cable – Connection Cable



## Technical data

Туре	RS 4.4T-2
ID no.	U2097
Connector A	Male, M12 × 1, Straight, A-code
Design specification	Acc. to IEC 61076-2-101
Number of contacts	4
Contacts	Bronze, CuSn, Gold-plated
Contact carriers	Plastic, TPU, Black
Connector body	Plastic, TPU, Yellow
Coupling nut	Brass, CuZn, Nickel-plated
Tightening torque (range)	0.8 1 Nm (note max. torque of mating connector!)
Mechanical life	> 100 Mating cycles
Pollution degree	3
Protection class (When coupled)	IP68, IP69K
	NEMA: 1, 3, 4, 6P
Cable data	
Cable ID	RF50516
Total number of conductors	4
Cable diameter	Ø 5.33 mm
Cable length (L)	2 m (+50mm or 4% of length/-0.0, Whichever is greater)
Cable jacket	PVC, Gray
Conductor diameter	0.054 "
Conductor material	TC (tinned copper)
Conductor insulation material	PVC

## **Features**








- ■M12, Male, Straight, 4-pin
- ■IP68, IP69K
- Instrumentation Tray Cable
- Gray PVC jacket, 4X22 AWG
- ■Sunlight Resistant
- ■-40 Cold Bend Rating
- ■Oil Resistant
- ■Flame Ratings: UL 1685 FT4, UL1061, CSA
- ■Flexlife® and C-Track Approved
- Cable length: 2 m

## Cable cross section



# Contact assignment

Connector A



#### Cable cross-section view



## Technical data

Conductor size	4 x 22 AWG [Similar to 0.34 mm <sup>2</sup> ]
Number of strands x O.D.	19 x 0.0058 "
Conductor colors	BN, WH, BU, BK
Electrical properties at +20 °C	
Rated voltage	250 V
Current	4 A
Mechanical and chemical properties	
Bending radius (static)	≥ 5 x Ø
Bending radius (dynamic)	≥ 10 x Ø
Cold bend rating	-40 °C
Flex rating 20 x Ø	10 million cycles*
	*When properly installed @ 20°C, 50%RH, and a cycle speed of ≤0.5 cycles per second.
C-Track	Yes
Ambient temperature range (static)	-40 °C+105 °C
Ambient temperature range (dynamic)	-40 °C+105 °C
Temperature range (installation)	-20 °C+105 °C
Approval	
Approvals	UL 2238 CSA C22.2 No. 182.3 CE RoHS
Note	
	<ul> <li>Flex ratings may be reduced if used in extreme temperatures, exposure to certain chemicals, operating above the rated cycle speed, or operating below the rated cable bend radius.</li> <li>We reserve the right to make technical</li> </ul>
	alterations without prior notice.

# Circuit Diagram

1	BN
2	WH
2 -	BU
3 -	ВК
4 -	

## Accessories

#### TORQUE-WRENCH-SET-M12-LEGACY A900153


Adjustable torque driver to connect to a Ø15mm knurl. Compatible with the redesigned and legacy M12 cordsets. Includes (1) adjustable torque driver, (1) adjustment tool, (1) 1/4"square to 4mm hex adaptor bit, and (1) Ø15mm spring loaded clamp bit



## Accessories

#### M12-CORDSETS-MOUNTING-CLIP-(10/BAG)

100016882



10 Pack of black mounting clips and M4x8mm mounting screws, used to secure cable to cable connection points.