

# CH \_ J \_ Class J fuse holder

The CH\_J\_ Class J fuse holders are available in 30 and 60 amp ratings featuring IP20 finger-safe construction that can be either DIN-Rail or panel mounted. Available as factory configured 1-, 2- or 3-pole holders they are available with optional open fuse indication to speed troubleshooting.

## **Ratings**

- Volts 600 V (or less)
- Amps
  - 30 A
  - 60 A
- SCCR 200 kA

# Bussmann 600 Bussmann 600 easyID easyID A WARNING

60 A

# Agency information

 UL Listed, Guide IZLT, File E14853, UL 4248/CSA 22.2 No. 4248.P, CE

30 A

### **Conductors**

 Single 1-18 AWG and dual 3-18 AWG Cu solid and stranded conductors

## **Terminal torque ratings**

- 10-18 AWG 24 lb-in
- 1-8 AWG 35 lb-in

### Storage and operating temperature range\*

- -20°C to +75°C
- \* For fuse selection on applications above or below 25°C, consult derating charts in the Bussmann Division publication no. 3002 "Selecting Protective Devices" (SPD)

### Flammability rating UL 94V0

### Catalog no. IP20 Volts finger-Amps Without indication\* With indication\*\* Poles (AC/DC) safe AWG Cu wire range **Padlockable** Mounting CH30J1 CH30J1I 1 CH30J2 CH30J2I 2 30 600 Yes Single 1-18, dual 3-18 35mm DIN/ panel 3 CH30J3 CH30J3I CH60J1 CH60J1I 1 2 CH60J2 CH60J2I 60 600 Yes Single 1-18, dual 3-18 Yes 35mm DIN/ panel CH60J3 CH60J3I 3

### **Features**

- Choice of local fuse indication; easyID<sup>TM</sup> viewing window (for seeing indicator on LPJ-SPI indicating fuse) or neon lamp
- Versatile 1-, 2- and 3-pole versions for 0-30 A and 35-60 A fuses with dual wire rated connections simplify wiring
- Improved electrical safety with IP20 finger-safe construction with lock-out/tag-out feature. 3-phase fuse extraction assures all phases are opened for service work
- Flexible panel/35mm DIN-Rail mounting

Dimensions — mm				
Fuse amps	Poles	W	D	Н
	1	32		
Up to 30 A	2	64	70	115
	3	96		
35-60 A	1	40		
	2	80	83	125
	3	120		

<sup>\*</sup> Local fuse indication 6 amps and above possible using Bussmann series LPJ\_SPI permanent indication fuses.

<sup>\*\*</sup>Neon indication non-fuse dependent, minimum voltage 90 V.