DATASHEET





AZ 335-02ZK-M20

- 1 Cable entry M 20 x 1.5
- Metal enclosure
- Long life
- Universal coding
- 40,5 mm x 114 mm x 38 mm
- Actuator heads can be repositioned in steps 4 x 90°
- Can be mounted on a flat surface
- High level of contact reliability with low voltages and currents
- Slotted holes for adjustment, circular holes for location

Data

Ordering data

Note (Delivery capacity) Not available!

eCl@ss number, Version 27-27-26-02

9.0

27-27-26-02 eCl@ss number, Version

11.0

General data

Coding level according to

ISO 14119

Low

Enclosure material Aluminium

Enclosure coating material painted

Material of the contacts,

Silver

electrical

Gross weight 225 g

General data - Features

Number of safety contacts 2

Safety appraisal

Standards EN ISO 13849-1

Mission Time 20 Year(s)

Safety appraisal - Safety outputs

B10d Normally-closed

contact (NC)

2,000,000 Operations

Mechanical data

Mechanical life, minimum 10,000,000 Operations

Latching force 5 N

positive break travel 10.7 mm

Positive break force,

minimum

5 N

Note (Positive break force) per NC

Mechanical data - Connection technique

Terminal Connector Screw connection

Cable section, minimum 0.75 mm²

Cable section, maximum 2.5 mm²

Note (Cable section) All indications about the cable section are including the conductor ferrules.

Mechanical data - Dimensions

Length of sensor 38 mm

Width of sensor 40.5 mm

Ambient conditions

Degree of protection

IP67 to EN 60529

Ambient temperature,

minimum

-30 °C

Ambient temperature,

maximum

+90 °C

Ambient conditions - Insulation value

Rated insulation voltage U_i 5

500 V

Rated impulse withstand

 $voltage U_{imp}$

6 kV

Electrical data

Thermal test current 10 A

Utilisation category AC-15 230 VAC

Utilisation category AC-15 4 A

Utilisation category DC-13 24 VDC

Utilisation category DC-13 4 A

Switching element Opener (NC)

Switching principle Creep circuit element

Scope of delivery

Notes

Note (General)

By turning the head in 90° steps, 8 actuating planes are possible. A Torx T10 screwdriver is required for this purpose. Even when the screw is removed, the head is self-retaining. The switch can still not be tampered.

Schmersal, Inc., 15 Skyline Drive, Hawthorne, NY 10532

The details and data referred to have been carefully checked. Images may diverge from original. Further technical data can be found in the manual. Technical amendments and errors possible.

Generated on: 11/9/2021, 9:00 AM