

## Spa Panels



## Contents

## Description

## Page

Overview .....	V1-T1-2
CH Specialty Products	
Spa Panels	
Surge Panel .....	V1-T1-16
Type CH Renovation Loadcenter .....	V1-T1-18
Type CH Retrofit Interior Kits .....	V1-T1-19
CH Loadcenter Options and Accessories .....	V1-T1-22
CH Circuit Breakers .....	V1-T1-36

## CH Specialty Products

## Spa Panels

## Product Description

Eaton's CH Spa Panels are premium factory-assembled "combination" units that provide ground fault protection, as well as a convenient way to turn spa pumps on and off. The NEC requires that all pool and spa pumps be protected by a ground fault interrupter and a disconnect switch mounted within 10 feet of the tub or the spa.

## Features

- Two extra circuits for additional loads
- Limited lifetime warranty
- UL Listed
- Tough powder-coated galvanized steel enclosure
- Factory-installed two-pole ground fault circuit interrupter (GFCI)

## Product Selection

## CH Spa Panel



## Single-Phase Three-Wire—120/240 Vac Insulated/Bondable Neutral—Factory-Installed Ground Bar

Main Ampere Rating	Circuit Breaker Included	Enclosure Type	Type of Trim Included	Box Size	Wire Size Range Cu/Al 60 °C or 75 °C for Main Lugs	Catalog Number
30	CH230GFT	Outdoor	—	5R	#14–1/0	CH30SPAST <sup>①</sup>
40	CH240GFT	Outdoor	—	5R	#14–1/0	CH40SPAST <sup>②</sup>
50	CH250GFT	Outdoor	—	5R	#14–1/0	CH50SPAST <sup>③</sup>
60	CH260GFT	Outdoor	—	5R	#14–1/0	CH60SPAST <sup>④</sup>

## Notes

- ① Includes a CH230GFT breaker, factory installed, and two extra circuits for convenience.  
 ② Includes a CH240GFT breaker, factory installed, and two extra circuits for convenience.  
 ③ Includes a CH250GFT breaker, factory installed, and two extra circuits for convenience.  
 ④ Includes a CH260GFT breaker, factory installed, and two extra circuits for convenience.

**Plug-on Ground Fault Circuit Breakers, Type CH 10 kAIC, 120 Vac and 120/240 Vac****Type CH Single-Pole****Type CH Ground Fault Circuit Breakers (5 Milliampere) 3/4-Inch (19.1 mm) per Pole 120 Vac or 120/240 Vac, 10 kAIC**

Ampere Rating	Wire Size Range Cu/Al 60 °C or 75 °C <sup>①</sup>	Catalog Number—1 per Shelf Carton	
		Single-Pole 120 Vac Requires One 3/4-Inch (19.1 mm) Space	Two-Pole 120/240 Vac Common Trip Requires Two 3/4-Inch (19.1 mm) Spaces
15	#14–6	CHFGFT115	CH215GFT
20	#14–6	CHFGFT120	CH220GFT
25	#14–6	CHFGFT125	CH225GFT
30	#14–6	CHFGFT130	CH230GFT
35	#14–6	—	CH235GFT
40	#14–6	—	CH240GFT
45	#14–6	—	CH245GFT
50	#14–6	—	CH250GFT
60	#14–6 <sup>①</sup>	—	CH260GFT

**Type CH Two-Pole****Type CH Ground Fault Equipment Protectors (30 Milliampere) 3/4-Inch (19.1 mm) per Pole 120 Vac or 120/240 Vac, 10 kAIC**

Ampere Rating	Wire Size Range Cu/Al 60 °C or 75 °C <sup>①</sup>	Catalog Number—1 per Shelf Carton	
		Single-Pole 120 Vac Requires One 3/4-Inch (19.1 mm) Space	Two-Pole 120/240 Vac Common Trip Requires Two 3/4-Inch (19.1 mm) Spaces
15	#14–6	CHFEP115	CH215EPD
20	#14–6	CHFEP120	CH220EPD
25	#14–6	CHFEP125	—
30	#14–6	CHFEP130	CH230EPD
40	#14–6	—	CH240EPD
50	#14–6	—	CH250EPD
60	#14–6 <sup>①</sup>	—	CH260EPD

**Type CH Switching Neutral Breakers—10 kAIC, 120 Vac and 120/240 Vac**

Used to open the neutral along power line(s) for applications of gas pumps.

**CH220SW****3/4-Inch (19.1 mm) per Pole 120/240 or 240 Vac, 10 kAIC**

Ampere Rating	Wire Size Range Cu/Al 60 °C or 75 °C	Catalog Number—1 per Shelf Carton	
		Two-Pole 120 Vac Common Trip Requires Two 3/4-Inch (19.1 mm) Spaces	Three-Pole 120/240 Vac Common Trip Requires Three 3/4-Inch (19.1 mm) Spaces
15	#14–8	CH215SW <sup>②</sup>	CH315SW <sup>③</sup>
20	#14–8	CH220SW <sup>②</sup>	CH320SW <sup>③</sup>
30	#14–8	CH230SW <sup>②</sup>	CH330SW <sup>③</sup>
40	#14–8	CH240SW <sup>②</sup>	CH340SW <sup>③</sup>
50	#14–8	CH250SW <sup>②</sup>	CH350SW <sup>③</sup>

**Notes**

- <sup>①</sup> 60 A breaker listed for 75 °C Cu wire only.  
<sup>②</sup> For circuit breakers with shunt trip, add ST suffix. Shunt trip requires one additional pole space.  
<sup>③</sup> Switching duty rated.