

DATASHEET

Variable Speed Drives



Main Features



Reference : CFW701E0107T5NBN1C3
 Product code : 12263889
 Product line : CFW701 HVAC

Basic data

Power supply : 500-600 V
 Input minimum-maximum voltage : 425-660 V
 Number of phases : 3
 Input : 3
 Output : 3

Supply voltage range	500-600 V		500-600 V	
Overload regime	Normal (ND)	Heavy (HD)	Normal (ND)	Heavy (HD)
Rated current	107A	90		
Overload current at 60 s	117,7A	117,7A		
Overload current at 3 s	160,5A	200		

Maximum applicable motor

Voltage/Frequency	Power (HP / kW) [1]	
	Normal Overload (ND)	Heavy Overload (HD)
525V / 50Hz	100 / 75	75 / 55
575V / 60Hz	100 / 75	75 / 55

Dynamic braking [2] : Optional without braking
 Electronic supply : Internal
 Safety Stop : No
 RFI internal filter [3] : With filter (C3 category)
 External filter : Not available
 Link Inductor : Yes
 Memory card : Not included in the product
 USB port : Yes, available in HMI
 Line frequency : 50/60Hz
 Line frequency range (minimum - maximum) : 48-62 Hz
 Phase unbalance : Less or equal to 3% of input rated line voltage
 Transient voltage and overvoltage : Category III
 Rated current of single-phase input :
 - Overload (ND) :
 - Overload (HD) :
 Rated current of three-phase input :
 - Overload (ND) : 107A
 - Overload (HD) : 90A
 Typical input power factor : 0,94
 Displacement factor : 0,98
 Rated efficiency : $\geq 98\%$
 Maximum connections (power up cycles - on/off) per hour : 60
 DC power supply : Allow
 Standard switching frequency :
 - Overload ND : 2 kHz
 - Overload HD : 2 kHz
 Selectable switching frequency : 1,25 and 2 kHz
 Real-time clock : Not available
 Copy Function : Yes, by MMF
 Dissipated power:

Mounting type	Overload		Overload (*)	
	ND	HD	ND	HD
Surface	1700 W	1441 W	Not applicable	Not applicable
Flange	315 W	276 W	Not applicable	Not applicable

Source available to the user

Output voltage : 24 Vcc
 Maximum capacity : 500 mA

Control/performance data

Power supply : Switched-mode power supply
 Control method - induction motor : V/f, VVW, Sensorless
 Encoder interface : Available in inverter
 Control output frequency [5] : 0 to 300 Hz
 Frequency resolution : Equivalent to 1 rpm

DATASHEET

Variable Speed Drives



Control/performance data

V/F Control	
- Speed regulation	: 1% of rated speed
- Speed variation	: 1:20
VVW Control	
- Speed regulation	: 1% of rated speed
- Speed variation	: 1:30
Sensorless vector control	
- Speed regulation	: 0,5% of rated speed
- Speed variation	: 1:100
Vector control with encoder	
- Speed regulation	: Not applicable
- Speed variation	: Not applicable

Analog inputs

Quantity (standard)	: 3
Levels	: 0-10V, 0/4-20mA and -10-+10V
Impedance	
- Impedance for voltage input	: 400 kΩ
- Impedance for current input	: 500 Ω
Function	: Programmable
Maximum allowed voltage	: ± 15 Vdc

Digital inputs

Quantity (standard)	: 8
Activation	: Active low and high
Maximum low level	: 2 V
Minimum high level	: 10 V
Input current	: 7.5 mA
Maximum input current	: 9.5 mA
Function	: Programmable
Maximum allowed voltage	: 30 Vcc

Analog outputs

Quantity (standard)	: 2
Levels	: 0 to 10V, 0 to 20mA and 4 to 20mA
RL for voltage output	: 10 kΩ
RL for current output	: 500 Ω
Function	: Programmable

Digital outputs

Quantity (standard)	: 2 NO/NC relay and 3 transistor
Maximum voltage	: 240 Vac and 30 Vdc
Maximum current	: 0.75 A and 80 mA
Function	: Programmable

Communication

- Modbus-RTU (Standard)
- Modbus/TCP (Not available)
- Profibus DP (with accessory: PROFIBUS DP-01)
- Profibus DPV1 (Not available)
- Profinet (Not available)
- CANopen (with accessory: CAN-01)
- DeviceNet (with accessory: CAN-01)
- EtherNet/IP (Not available)
- EtherCAT (Not available)
- BACnet (Not available for CFW700 series. Available by default on the CFW701 series)

Protections available

- Output overcurrent/short circuit
- Power supply phase loss
- Under/Overvoltage in power
- Overtemperature
- Motor overload
- IGBT's modules overload
- Fault/External alarm
- Output phase-ground short-circuit
- CPU or memory failure

Operation interface (HMI)

Avaliability	: Included in the product
HMI installation	: Local
Number of HMI buttons	: 9
Display	: Graphic LCD
Indication accuracy	: 5% of rated current
Speed resolution	: 1 rpm
Standard HMI degree of protection	: IP56
HMI battery type	: Not applicable
HMI battery life expectancy	: Not applicable

DATASHEET

Variable Speed Drives



Operation interface (HMI)

Remote HMI type : Detachable of the inverter
Remote HMI frame : Accessory
Remote HMI degree of protection : IP56

Ambient conditions

Enclosure : NEMA1
Pollution degree : 2 (EN50178 and UL508C)
Temperature
- Minimum : -10 °C / 14 °F
- Nominal [4] : 45 °C / 113 °F
Current reduction factor [5] : 2 % per °C of 45 (113) to 55 °C (131 °F)
Relative humidity (non-condensing)
- Minimum : 5%
- Maximum : 95%
Altitude
- Rated conditions : 1000 m (3281 ft)
- Maximum allowed for operation (with derating factor) : 4000 m (13123 ft)
Current Reduction factor[6]
- Current derating factor (for altitudes above rated) : 1% for each 100 m above (0,3% for each 100 ft above)
- Voltage derating factor (for altitudes above 2000 m / 6562 ft) : 1,1% for each 100 m above (0,33% for each 100 ft above)

Sustainability policies

RoHS : Yes
Conformal Coating : 3C2 (IEC 60721-3-3:2002)

Dimensions

Size : E
Height : 735 mm / 28.9 in
Width : 335 mm / 13.2 in
Depth : 358 mm / 14.1 in
Weight : 65 kg / 143.3 lb

Mechanical installation

Mounting position : Surface or flange
Fixing screw : M8
Tightening torque : 20 N.m / 14.76 lb.ft
Allows side-by-side assembly : No
Minimum spacing around the inverter
- Top : 110 mm / 4.33 in
- Bottom : 130 mm / 5.12 in
- Front : 20 mm / 0.78 in
- Between inverters (IP20) : 40 mm / 1.57 in

Electrical connections

Cable gauges and tightening torque:

	Recommended cable gauge to 75 °C (167 °F)	Recommended tightening torque
Power	50,0 mm ² (1 AWG) HD	15 N.m / 11.07 lb.ft
Braking	Not applicable	15 N.m / 11.07 lb.ft
Grounding	35,0 mm ² (2 AWG)	10 N.m / 7.38 lb.ft
Control	0,5 to 1,5 mm ² (20 to 14 AWG)	0,5 N.m / 0.37 lb.ft

Additional specifications

Maximum breaking current : Not available
Minimum resistance for the brake resistor : Not available
Recommended aR fuse [6] : FNH00-160K-A
Recommended aR fuse [6] : Not applicable
Recommended circuit breaker [6] : To define
Recommended circuit breaker [6] : Not applicable

Standards

Safety	<ul style="list-style-type: none">- UL 508C - Power conversion equipment.- UL 840 - Insulation coordination including clearances and creepage distances for electrical equipment.- EN 61800-5-1 - Safety requirements electrical, thermal and energy.- EN 50178 - Electronic equipment for use in power installations- EN 60204-1 - Safety of machinery. Electrical equipment of machines. Part 1: General requirements. Note: To have a machine in accordance with this standard, the machine manufacturer is responsible for installing an emergency stop device and supply disconnecting device.- EN 60146 (IEC 146) - Semiconductor converters.- EN 61800-2 - Adjustable speed electrical power drive systems - Part 2: General requirements - Rating specifications for low voltage adjustable frequency AC power drive systems.
Electromagnetic compatibility	EN 61800-3 - Adjustable speed electrical power drive systems - Part 3: EMC product standard including specific test methods.



	<ul style="list-style-type: none">- EN 55011 - Limits and methods of measurement of radio disturbance characteristics of industrial, scientific and medical (ISM) radio-frequency equipment.- CISPR 11 - Industrial, scientific and medical (ISM) radio-frequency equipment - Eletromagnetic disturbance characteristics - Limits and methods of measurement.- EN 61000-4-2 - Eletromagnetic compatibility (EMC) - Part 4: Testing and measurement techniques - Section 2: Eletrostatic discharge immunity test.- EN 61000-4-3 - Eletromagnetic compatibility (EMC) - Part4: Testing and measurement techniques - Section 3: Radiated, radio-frequency, electromagnetic field immunity test.- EN 61000-4-4 - Eletromagnetic compatibility (EMC) - Part4: Testing and measurement techniques - Section 4: Electrical fast transient/burst immunity test.- EN 61000-4-5 - Eletromagnetic compatibility (EMC) - Part4: Testing and measurement techniques - Section 5: Surge immunity test.- EN 61000-4-6 - Eletromagnetic compatibility (EMC) - Part4: Testing and measurement techniques - Section 6: Immunity to conducted disturbances, induced by radio-frequency fields.
Mechanical construction	<ul style="list-style-type: none">- EN 60529 - Degrees of protection provided by enclosures (IP code).- UL 50 - Enclosures for electrical equipment.- EN 60529 e UL 50

Certifications

- Notes**
- 1) Orientative motor power, valid for WEG Motors standard of IV poles. The correct sizing must be done according to the nominal current of the motor used, which must be less than or equal to the rated output current of the inverter;
 - 2) Braking resistor is not included;
 - 3) With category for emission level conducted;
 - 4) Without derating and with minimum spaces;
 - 5) For temperatures above the nominal and maximum temperature (with derating of current and minimum spaces);
 - 6) For altitude over of specified;
 - 7) All images are merely illustrative;
 - 8) For more information, see the users manual of the CFW700 (size E).